


47/65322 120



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 700 218 A2

(12) EUROPEAN PATENT APPLICATION

(43) Date of publication:
06.03.1996 Bulletin 1996/10

(51) Int Cl.⁶: H04N 9/73

(21) Application number: 95630020.6

(22) Date of filing: 09.03.1995

(84) Designated Contracting States:
DE FR GB IT

(30) Priority: 04.08.1994 KR 9419283

(71) Applicant: LG ELECTRONICS INC.
Seoul (KR)

(72) Inventors:


- Yoon, Sang Han,
No. 101-101 Dongseo Mansions
Taegu (KR)
- Ha, Young Ho,
No. 103-1101 Chunggoo Apartment
Taegu (KR)

(74) Representative: Waxweiler, Jean et al
Denemeyer & Associates Sàrl
P.O. Box 1502
L-1015 Luxembourg (LU)

(54) Image compensation system for video appliances and methods thereof

(57) An image compensation system and methods for video appliances to reproduce an optimum image, by judging exterior environment and by compensating for an original image by the judged exterior environment. According to the system and methods, a color sensor senses color of exterior lighting of an appliance, and provides electrical signals corresponding to color components of the sensed color. The signals are converted into a digital value by an analog-to-digital converter. A microprocessor judges the type of exterior lighting, by the digitized values, and searches for image compensation data according to the judged exterior lighting. It thereby makes a video processor compensate for an original image signal.

FIG. 2



Description

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to an image compensation system and methods for video appliances, such as a color television receiver, etc., which compensates automatically for hue, saturation, contrast, brightness, and white balance of an image, corresponding with the exterior environment of the appliance.

2. Description of the Prior Art

Conventional video appliances, especially a television receiver generally adopts a skin color compensation circuit and an automatic brightness control circuit, as an image signal processor.

The skin color compensation circuit analyzes a received image signal, and if the signal is judged as a human skin color, the circuit provides a prescribed color, i.e., a skin color.

In practice, users often control human skin color when adjusting the picture of a television receiver. Skin color plays a standard part in adjusting the color of a picture.

The skin color compensation circuit, however, cannot properly cope with the variety of skin colors, because it merely checks without regard to exterior lightings whether or not an image signal is a skin color.

And it works in the same manner on colors analogous to skin color.

Therefore, an error in color reproduction may arise, and accordingly there will be some limiting factors on natural color reproduction.

The automatic brightness control circuit controls the brightness of a picture by sensing exterior brightness.

The attached FIG. 1 shows a block diagram of a television receiver adopting the automatic brightness control circuit.

The television receiver is, with reference to FIG. 1, composed of a tuner 1 for tuning to an aiming station in broadcasting signals received by an antenna; an intermediate-frequency (hereinafter an "IF") signal processor 2 for processing an IF signal transformed from the tuned signal; a detector 3 for detecting an image signal and an audio signal from the IF signal processor 2; an audio processor 4 for processing the audio signal detected from the detector 3; a speaker 5 for making audio sound from the processed audio signal; a key selector 6, such as key matrix, a remote control or the like, for providing a user's key instruction; a microprocessor unit (hereinafter an "MPU") 7 for allowing the tuner 1 to select an aiming station according to a user's key instruction, and for adjusting brightness of a picture by controlling the following video processor 8, corresponding with exterior brightness detected by the following brightness detector 10; a

video processor 8 for controlling the brightness of a picture under the control of the MPU 7; a picture tube 9 for displaying the image processed by the video processor 8; and a brightness detector 10 for detecting exterior brightness, which provides it to the MPU 7.

In operation, the MPU 7 controls the tuner 1 to select an aiming station according to the instruction from the key selector 6. The selected station signal is transformed into an IF signal at the IF signal processor 2. The IF signal is provided to the detector 3.

The detector 3 detects an image signal and an audio signal from the IF signal and provides the image signal to the video processor 8 and the audio signal to the audio processor 4.

The audio processor 4 performs amplification of the audio signal and various functions, such as stereo reproduction or multivoice processing, and provides the processed signal to the speaker 5.

The video processor 8 performs amplification of the image signal and processing a color signal and a luminance signal, and provides the processed signals to the picture tube 9.

The brightness detector 10 detects exterior brightness using a sensor, such as a photoconductive cell (CdS), and converts the detected signal into a digital signal by an analog-to-digital converter built in the brightness detector 10.

The digitized signal is provided to the MPU 7. The MPU 7 performs an appropriate operation by using original brightness data CD, exterior brightness data C1, and reference data C0, e.g. $CD = CD \times C1/C0$, and provides the resulting value to the video processor 8.

The video processor 8 compensates for the brightness data CD in accordance with the exterior brightness data C1, and thereby the brightness of the picture tube 9 can be adjusted.

In such an automatic brightness control circuit, however, it is difficult to perform sufficient natural color reproduction because the circuit processes brightness (or contrast) only.

In fact, it is necessary to control all the image reproduction factors, i.e. hue, saturation, contrast, brightness, and white balance, for complete natural color reproduction. Without collective control of these factors, it is impossible to accomplish natural color reproduction, and it is difficult to properly represent an image bearing natural colors.

SUMMARY OF THE INVENTION

The present invention, which is directed to avoiding such a problem, reproduces an optimum image and performs complete natural color reproduction, by judging the exterior environment by sensing exterior lighting, and compensating for an original image based on the judged exterior environment.

According to one feature of this invention, there is provided an image compensation system for video ap-

pliances, comprising:

means for sensing a color of exterior lighting and for providing electrical signals corresponding to color components of said sensed color;

an analog-to-digital converter for converting the output signals of said color sensing means into a digital value;

means for processing the output signal of said analog-to-digital converter under the instruction of a prepared program, having (i) a memory for memorizing image compensation data corresponding to the color of exterior lighting, (ii) means for searching for corresponding data among said image compensation data, reading the output of said analog-to-digital converter, and (iii) means for outputting the searched data; and

means for compensating for an original image signal utilizing the output signal of said processing means.

According to another feature of this invention, there are provided image compensation methods for video appliances, comprising the steps of;

sensing a color of exterior lighting and providing electrical signals corresponding to color components of said sensed color;

digitizing said electrical signals corresponding to said color components;

judging exterior environment from said digitized signal;

searching for image compensation data corresponding to said exterior environment; and

compensating for an original image signal utilizing said image compensation data.

BRIEF DESCRIPTION OF THE DRAWINGS

These and other features, aspects, and advantages of the present invention will become better understood with regard to the following description, appended claims, and accompanying drawings where:

FIG. 1 is a block diagram of a television receiver adopting a conventional automatic brightness control circuit;

FIG. 2 is a block diagram of a television receiver adopting an image compensation system of the present invention;

FIG. 3 is a detailed block diagram of a color sensor/processor depicted in FIG. 2;

FIG. 4 is a flowchart explaining the general operation of the present invention;

FIG. 5 is a table showing the output value of color components from a color sensor, according to an exterior environment;

FIG. 6 is a view showing conditions of an exterior

environment for storing data;

FIGs. 7A and 7B are tables showing image compensation data according to the summation of color components; and

FIGs. 8A and 8B are flowcharts explaining the operation of another embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The operation of the present invention will be discussed with regard to FIG. 2 through FIG. 7.

Referring to FIG. 2, the system according to the present invention, an image compensation system for video appliances, is composed of; a tuner 100 for tuning to an aiming station in broadcasting signals received by an antenna; an IF signal processor 200 for processing an IF signal transformed from the tuned signal; a detector 300 for detecting an image signal and an audio signal from the IF signal processor 200; an audio processor 400 for processing the audio signal detected from the detector 300; a speaker 500 for making audio sound from the processed audio signal; a key selector 600, such as a key matrix, a remote control or the like, for providing a user's key instruction; an MPU 700 for allowing the tuner 100 to select an aiming station in accordance with a user's key instruction, and for adjusting brightness of a picture by controlling the following video processor 800, corresponding with exterior lightings and colors detected by the following color sensor/processor 1000; a video processor 800 for compensating for an original image signal under the control of the MPU 700; a picture tube 900 for displaying the image signal processed by the video processor 800; and a color sensor/processor 1000 for sensing and processing the exterior lightings and colors.

The color sensor/processor 1000 includes, referring to FIG. 3, a color sensor 11A for decomposing incident light into the three primary colors, i.e., red, green, and blue; an amplifier 11B for amplifying the color signals from the color sensor 11A; a low-pass filter 11C for eliminating noise from the amplified color signal; an analog-to-digital converter 11D for converting the analog color signal from the low-pass filter 11C into a digital signal.

The analog-to-digital converter is represented as an 'ADC' in the drawings for briefness. It may be equipped in the MPU 700 accordingly as the function of a microcomputer or microprocessor has recently been expanded.

The operation of such a constructed system, an image compensation system for video appliances, will be described with reference to FIGs. 2 and 3 and a flowchart in FIG. 4.

The MPU 700 controls the tuner 100 to select an aiming station in broadcasting signals according to the

instruction from the key selector 600. The selected station signal is transformed into an 1F signal at the IF signal processor 200, and is provided to the detector 300.

The detector 300 detects an image signal and an audio signal from the IF signal, and provides the audio signal to the audio processor 400 and the image signal to the video processor 800.

The audio processor 400 performs amplification of the audio signal and various functions, such as stereo reproduction or multivoice processing, and provides the processed signal to the speaker 500.

The video processor 800 performs amplification of the image signal and processing a color signal and a luminance signal, and provides the processed signals to the picture tube 900.

The color sensor/processor 1000 senses the color of exterior lightings, such as sunlight or any other artificial light, and amplifies the color signal and rejects noise. Thereafter the color sensor/processor 1000 provides the processed signal to the analog-to-digital converter 11D as color data.

The MPU 700 finds the current exterior lighting environment using the digitized color data. It thereafter provides a properly compensated image data (hue, saturation, contrast, brightness, and white balance) to the video processor 800.

Specifically, with reference to FIG. 3, the color sensor 11A decomposes the exterior lighting, such as sunlight or any other artificial light, into red (R), green (G), and blue (B). Because the output level of the color sensor is weak, it is provided to the low-pass filter 11C after being amplified by the amplifier 11B.

The low-pass filter 11C produces a purified color signal by eliminating noise from the signal outputted from the amplifier 11B (in the case of light bearing a low-frequency flicker, there is noise similar to a sinusoidal wave),

The color signal passing through the low-pass filter 11C is converted into a digital signal at the analog-to-digital converter 11D, and is provided as color data to the MPU 700.

The color data being provided, the MPU 700 analyzes current exterior lightings, and provides proper color compensation data to the video processor 800 using the result of analysis.

In general, colors of R, G, and B are called the three primary colors of light. By changing the mix ratio of the colors, almost all of the colors can be represented on a picture tube. For instance, in the case of white color, the projection degree of R, G, and B is '1', respectively; in the case of grey color, the projection degree is '0.5', respectively. If the three colors are not projected, black color is represented.

In contrast, a color sensor decomposes incident light into R, G and B, and provides electrical signals proportional to the amount of the color components.

FIG. 5 shows an exemplary relative data of the output value of R, G, and B where exterior environment is

a fluorescent lamp, an incandescent lamp, sunlight, or no light (darkroom).

The above data are served as reference data for judgement of what the current exterior environment is, which are stored in a memory in a microprocessor.

The general operation of the present invention will be described with reference to a flowchart in FIG. 4.

The MPU 700 reads a quantized color data (digitized output of the color sensor) directing the current exterior lightings, and judges thereby the exterior environment mode. If it finds thereafter an original image mode to be outputted by retrieving the color data entering the video processor 800, and compares the original image mode with the exterior environment mode,

Here, although image compensation can be performed for all of the quantized color data from the color sensor, a processing sequence may become too complicated. In addition, because human eyesight is, as matter of fact, not able to distinguish delicate color differences, only the artificial light used for common homes and natural light (including weather conditions and times) were taken into consideration.

That is, as shown in FIG. 6, taking a fine day, a cloudy day, a rainy day, a morning, a noon, an evening, a night, a fluorescent lamp, an incandescent lamp, and no light (a darkroom) as factors for judgement to exterior environment, 36 kinds of exterior environment modes can be set. Since the correlation between night and weather is low and if the case that similar outputs are provided is considered, the number of cases may be reduced to an appropriate extent.

The exterior environment mode may be determined not only when the color data from the color sensor 11A is completely in accord with the prescribed reference data but also when the color data lies within the prescribed range.

In such cases, the MPU 700 compares the original image mode to be outputted with the exterior environment mode now being inputted.

If the two modes are the same, the MPU 700 outputs the untreated original image data to the video processor 800, and maintains the original image mode.

If the two modes are different, the MPU 700 compensates for the original image data by the determined exterior environment mode, and provides the compensated image mode to the video processor 800. Accordingly, the compensated image bearing the optimum hue, saturation, brightness, contrast, and white balance, which are in accordance with the exterior environment, is displayed on the picture tube 900.

Taking a set whose brightness step, saturation step, and contrast step respectively range from 0 to 62 and hue step ranges from -31 to +31 as an actual example, the set provides an image of hue=0, saturation=31, brightness=31, contrast=62, and white balance=9000K in the case of no light (a darkroom); the set provides an image of hue=-5, saturation=26, brightness=60, contrast=62, and white balance=10000K in the case of an

incandescent lamp.

Such data is based upon actual measurement. Although it may have a slight difference on the effect of any other environmental factor rather than illuminance or lighting, it deserves acceptance when considering human eyesight.

Since lighting of an incandescent lamp is brighter than lighting of no light, i.e., a darkroom, brightness of a picture must be strengthened. Since a red color component of an incandescent lamp is larger, a red color signal must be relatively reduced by controlling hue and saturation of a picture. Thus, there appears different data in each mode.

The representative feature of the embodiment so far discussed is to find the exterior environment by reading quantized color (R, G, and B) signals from a color sensor, and thereby to compensate for an original image,

Another embodiment compensating for received image data will be disclosed with reference to FIGs. 7A and 7B and FIGs. 8A and 8B.

This embodiment relates to image compensation methods which compensate for an image data by computing the summation of the electrical value of the quantized or digitized color signal (R, G, and B), or by judging the magnitude of R and B and the correlation between them.

The summation (S) of the value of the quantized color signals R, G, and B (in the case of 6-bit, 0-64) correlates with illuminance of the exterior lighting. From the value S, an image compensation data is, as a first step, determined, and thereby the original image data is compensated for. Thereafter, as a second step, white balance is compensated for by the value B-R or R-B as shown in FIG. 7B.

Specifically, FIG. 7A shows image compensation data of a set whose contrast step ranges from 30 to 100, brightness step ranges from 40 to 60, saturation step ranges from 40 to 55, and sharpness step ranges from 30 to 60. As first image compensation data, the data are determined according to the summation of R, G, and B, i.e., the illuminance of exterior lighting.

FIG. 7B shows, as second image compensation data, that if the summation of the quantized R, G, and B lies within a regular range, the data are determined by the difference and correlation between R and B.

The second image compensation data additionally compensates for white balance of a picture and accordingly accomplishes complete color reproduction according to the exterior lightings.

The system according to this embodiment reads the analog-to-digital quantized value from the color sensor, and computes R-B or B-R. Thereafter, it compares the value of R-B or B-R with G of exterior lighting, and thereby searches for image compensation data for brightness, saturation, contrast, sharpness, white balance in a software table. The found image compensation data compensates for the original image data. Here, the reason for computing both R-B and B-R is that the software

method is not capable of dealing with a negative computation.

FIGs. 8A and 8B show flowcharts explaining the operation of this embodiment, based upon the tables indicated in FIGs. 7A and 7B. The flowcharts indicate how compensation data, according to the values of R, G, and B from the color sensor, are produced.

From the foregoing, the present invention measures image data, such as hue, contrast, brightness, saturation, white balance, changing the conditions of exterior lightings. And it establishes a data base by the measured data. The data base is stored in a memory in a micro-processor.

The present invention determines current exterior environment using the measured data from the data base, and automatically compensates for hue, saturation, contrast, brightness, and white balance of a picture.

Accordingly, an image is reproduced with complete fidelity, and therefore a high-quality picture can be produced.

Claims

1. An image compensation system for video appliances, comprising:
 - means for sensing a color of exterior lighting to provide electrical signals corresponding to color components of said sensed color;
 - an analog-to-digital converter for converting said electrical signals from said color sensing means into a digital value;
 - means for processing the output signal of said analog-to-digital converter under the instruction of a prepared program, including (i) a memory for memorizing image compensation data corresponding to the color of exterior lighting, (11) means for reading the output of said analog-to-digital converter to search for corresponding data among said image compensation data, and (iii) means for outputting the searched data; and
 - means for compensating for an original image signal utilizing the output signal of said processing means.
2. The system according to claim 1, wherein said analog-to-digital converter is built in said memory of said processing means.
3. An image compensation system for video appliances, comprising:
 - means for sensing a color of exterior lighting to provide electrical signals corresponding to color components of said sensed color;
 - an amplifier for amplifying said signal from said color sensing means;
 - a noise rejection filter for eliminating noise from the amplified signal from said amplifier;

an analog-to-digital converter for converting the output signal of said noise rejection filter into a digital value;

means for processing the output signal of said analog-to-digital converter under the instruction of a prepared program, including (i) a memory for memorizing an image compensation data corresponding to the color of exterior lighting, (ii) means for reading the output of said analog-to-digital converter to search for a corresponding data among said image compensation data, and (iii) means for outputting the searched data;

means for compensating for an original image signal utilizing the output signal of said processing means.

4. An image compensation system for a color television receiver, comprising;

means for providing key instructions according to a user's key selection;

means for tuning to an aiming station for received broadcasting signals;

means for transforming the output signal of said tuning means into an intermediate-frequency signal, and for processing said intermediate-frequency signal;

means for detecting an image signal and an audio signal from said intermediate-frequency signal;

means for processing said detected audio signal to produce audio sound;

means for sensing a color of exterior lighting and for providing electrical signals corresponding to color components of said sensed color;

an analog-to-digital converter for converting the output signals of said color sensing means into a digital value;

means for processing the output signal of said analog-to-digital converter under the instruction of a prepared program, including (i) a memory for memorizing image compensation data corresponding to the color of exterior lighting, (ii) means for reading the output of said analog-to-digital converter to search for corresponding data among said image compensation data, and (iii) means for outputting the searched data;

means for compensating for an original image signal utilizing the output signal of said processing means; and

means for displaying said compensated image signal from said compensating means.

5. An image compensation method for video appliances, comprising the steps of:

sensing a color of exterior lighting and providing electrical signals corresponding to color components of said sensed color;
digitizing said electrical signals corresponding

to said color components;

judging an exterior environment from said digitized signal;

searching for an image compensation data corresponding to said exterior environment; and
compensating for an original image signal utilizing said image compensation data.

6. An image compensation method for video appliances, comprising the steps of:

sensing a color of exterior lighting and providing electrical signals corresponding to color components of said sensed color;

digitizing said electrical signals corresponding to said color components;

determining an image compensation data, having the substeps of (i) summing said digitized color components, (ii) judging exterior environment corresponding to said summed value, and (iii) producing said image compensation data corresponding to said judged exterior environment; and
compensating for an original image signal utilizing said image compensation data.

7. An image compensation method for video appliances, comprising the steps of:

sensing a color of exterior lighting and providing electrical signals corresponding to color components of said sensed color;

digitizing said electrical signals corresponding to said color components;

determining image compensation data, having the substeps of (i) summing said digitized color components, (ii) judging exterior environment corresponding to said summed value, (iii) producing first image compensation data corresponding to said judged exterior environment, (iv) judging the quantity of said summed value and a correlation between said color components, and (v) producing second image compensation data corresponding to said judged quantity and said correlation; and

compensating for an original image signal utilizing said first and second image compensation data.

FIG. 1 (PRIOR ART)




FIG. 2




FIG. 3




FIG. 4




FIG. 5

EXTERIOR ENVIRONMENT	RED	GREEN	BLUE
FLUORESCENT LAMP	1.0	0.7	0.7
INCANDESCENT LAMP	0.8	0.3	0.4
DAYLIGHT	2.8	2.4	4.8
DARKROOM	0.4	0	0.2
⋮	⋮	⋮	⋮

FIG. 6




FIG. 7A

SUM OF R,G & B (S) ITEM	$0 \leq S < 2$ (0-10 lux)	$2 \leq S < 10$ (10-30 lux)	$10 \leq S < 20$ (30-50 lux)	$20 \leq S < 31$ (50-70 lux)	$31 \leq S < 37$ (70-85 lux)	$37 \leq S < 45$ (85-100 lux)	$45 \leq S$ (100 lux-)
CONTRAST	30	40	55	70	85	93	100
BRIGHTNESS	40	42	46	50	54	57	60
SATURATION	40	41	45	48	51	53	55
SHARPNESS	30	33	39	45	51	55	60
LIGHTING	NO LIGHT (DARKROOM)	INDIRECT (1)	INDIRECT (2)	STANDARD	STRONG (1)	STRONG (2)	DAY- LIGHT
COMPENSATION STEP	FIRST	SECOND	THIRD	FOURTH	FIFTH	SIXTH	SEVEN- TH

FIG. 7B

VALUE OF R,G & B		WHITE BALANCE (COLOR TEMPERATURE)	COLOR COORDINATE		LIGHTING
			X	Y	
$R+G+B \geq 45$		13000 K	266	280	DAYLIGHT
$R+G+B < 2$		9000 K	270	284	DARKROOM
$2 \leq R+G+B < 45$	$0 \leq B-R$	12000 K	274	289	FLUORESCENT LAMP
	$1 \leq R-B \leq 4$	11000 K	279	296	FLUORESCENT LAMP + INCANDESCENT LAMP
	$5 \leq R-B$	10000 K	285	303	INCANDESCENT LAMP

FIG. 8A





FIG. 8B





(19)

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 700 218 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
02.01.1997 Bulletin 1997/01

(51) Int Cl.⁶: H04N 9/73

(43) Date of publication A2:
06.03.1996 Bulletin 1996/10

(21) Application number: 95630020.6

(22) Date of filing: 09.03.1995

(84) Designated Contracting States:
DE FR GB IT

(30) Priority: 04.08.1994 KR 9419283

(71) Applicant: LG ELECTRONICS INC.
Seoul (KR)

(72) Inventors:
• Yoon, Sang Han, No. 101-101 Dongseo Mansions
Taegu (KR)


• Ha, Young Ho,
No. 103-1101 Chunggoo Apartment
Taegu (KR)

(74) Representative: Waxweiler, Jean et al
Dennemeyer & Associates Sàrl
P.O. Box 1502
1015 Luxembourg (LU)

(54) Image compensation system for video appliances and methods thereof

(57) An image compensation system and methods for video appliances to reproduce an optimum image, by judging exterior environment and by compensating for an original image by the judged exterior environment. According to the system and methods, a color sensor senses color of exterior lighting of an appliance, and provides electrical signals corresponding to color compo-

nents of the sensed color. The signals are converted into a digital value by an analog-to-digital converter. A microprocessor judges the type of exterior lighting, by the digitized values, and searches for image compensation data according to the judged exterior lighting. It thereby makes a video processor compensate for an original image signal.

FIG. 2



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 95 63 0020

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. CL. 6)
X	US-A-5 289 268 (SUZUKI & AL.)	1,5	H04N9/73
Y	* column 1, line 49 - line 68 *	3	
A	* column 3, line 61 - column 5, line 29 *	2,4,6,7	

A	EP-A-0 599 495 (CANON INFORMATION SYSTEMS)	1,2,4-7	
Y	* column 4, line 49 - column 5, line 51 *	3	
	* column 11, line 24 - column 12, line 9; figures 3,8,9 *		

A	DE-A-27 19 086 (NORDDEUTSCHE MENDE RUNDfunk KG)	1-7	
	* page 4, line 1 - page 5, line 2 *		

A	PATENT ABSTRACTS OF JAPAN vol. 17, no. 39 (E-1311), 25 January 1993 & JP-A-04 257194 (SONY), 11 September 1992, * abstract *	1-7	

A	PATENT ABSTRACTS OF JAPAN vol. 10, no. 164 (E-410), 11 June 1986 & JP-A-61 016691 (SHARP), 24 January 1986, * abstract *	1-7	TECHNICAL FIELDS SEARCHED (Int. CL. 6)
	---		H04N
A	PATENT ABSTRACTS OF JAPAN vol. 10, no. 379 (E-465), 18 December 1986 & JP-A-61 172495 (SONY), 4 August 1986, * abstract *	1-7	

The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 7 November 1996	Examiner Pigniez, T
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1501 (01.11.1994)